

MIT Open Access Articles

*Mode retrieval from intensity profile
measurements using irradiant waveguide-modes*

The MIT Faculty has made this article openly available. **Please share**
how this access benefits you. Your story matters.

Citation: Idei, H. et al. "Mode retrieval from intensity profile measurements using irradiant waveguide-modes." Infrared, Millimeter, and Terahertz Waves, 2009. IRMMW-THz 2009. 34th International Conference on. 2009. 1-2. © Copyright 2010 IEEE

As Published: <http://dx.doi.org/10.1109/ICIMW.2009.5324607>

Publisher: Institute of Electrical and Electronics Engineers

Persistent URL: <http://hdl.handle.net/1721.1/59396>

Version: Final published version: final published article, as it appeared in a journal, conference proceedings, or other formally published context

Terms of Use: Article is made available in accordance with the publisher's policy and may be subject to US copyright law. Please refer to the publisher's site for terms of use.



Mode Retrieval from Intensity Profile Measurements using Irradiant Waveguide-modes

H. Idei^a, M. A. Shapiro^b, R. J. Temkin^b, T. Shimozuma^c, S. Kubo^c

^a Research Institute for Applied Mechanics, Kyushu University, Kasuga, 816-8560, Japan

^b Massachusetts Institute of Technology, Cambridge, MA 02139, USA

^c National Institute for Fusion Science, Toki, 509-5292, Japan

Abstract—The fields radiated from the waveguide were used to analyze propagating mode content in an oversized circular corrugated waveguide. The radiated fields were calculated by the Kirchhoff integral in the paraxial approximation. The irradiant waveguide modes of the radiated field are orthogonal within the paraxial approximation. The complex fractions in the irradiant mode expansion were deduced from an iteration process in which the reconstructed amplitude profile from the complex fractions coincided with the measured amplitude profile.

I. INTRODUCTION

ELECTRON Cyclotron Heating (ECH) using high power millimeter waves is an attractive method for plasma production, auxiliary heating, and current drive in a nuclear fusion research. A Gaussian beam from a high power gyrotron oscillator is coupled into oversized circular corrugated waveguides in the ECH system, which is transmitted to the launcher using the HE₁₁ mode of the waveguide. To obtain high transmission efficiency in the waveguide, the beam center-position and tilt in the coupling into the waveguide line should be aligned within tolerable limits to provide coupling into the HE₁₁ mode from the Gaussian beam. The offset or tilted injection excites unwanted coupling higher modes, which cause high transmission losses and arcing events in the high power transmission. The analysis of the mode content transmitted in the waveguide is a key issue to study how to attain the high coupling and transmission efficiencies.

In order to convert the output beam from the gyrotron into a Gaussian beam, the phase-correcting mirror system has been developed. The phase-correcting mirror has been designed using the phase profiles retrieved from the intensity profiles, when precise phase measurements are unavailable in the high power application. In the retrieval process, the field are evaluated at a few propagating position. This retrieval process was experimentally verified by direct phase measurements at a low power level [1]. Similar technique to the phase retrieval were used to analyze the mode content in the waveguide by using the radiated field from the waveguide [2]. The phase profiles were retrieved from the intensity profiles. The field at the waveguide aperture was calculated from the retrieved phase and intensity profiles, and the mode content was analyzed at the waveguide aperture. A new approach to analyze the mode content in the waveguide was proposed for the low power experiments where precise direct phase measurements were available [3]. The mode content of the waveguide modes was evaluated using the irradiant waveguide modes in the radiated field. In this method, the phase retrieval process was not required.

In this paper, the new approach using the irradiant waveguide modes is extended to use in the high power application where the phase measurements are unavailable. The mode content is directly retrieved from evolution of the amplitude profiles along the propagation, without the phase measurements and the phase retrieval process.

II. EXPERIMENTAL SETUP AND RESULTS

A Gaussian beam was prepared to inject to a 1m long corrugated waveguide with a diameter of 88.9mm. This injected beam was tilted by 1 degree with respect to the waveguide z -axis in the x -direction. The electric field was in y -direction, in perpendicular to the tilted x - z plane. Here, the wave frequency of the beam was 84 GHz. In the tilted injection, the unwanted modes were excited. The distorted intensity profiles were measured at the several propagation position along the z -axis. Figure 1 shows the intensity x - y profiles measured at $z = 150$ mm. The intensity pattern of the output beam was off-center in the x -direction. The phase profiles were retrieved from the measured intensity profiles by the iteration method in ref.3.

III. IRRADIANT WAVEGUIDE MODE EXPANSION

The field radiated from the waveguide was used to analyze the mode content transmitted in the waveguide. The radiated fields were calculated by the Kirchhoff Integral in the paraxial approximation. The irradiant waveguide modes Φ_{mn} which are the radiated waveguide eigen modes ϕ_{mn} at the z position were expressed as

$$\Phi_{mn}(x, y) = \frac{ik}{2\pi z} \int dx' dy' \phi_{mn}(x', y') \times \exp\left[-\frac{ik[(x' - x)^2 + (y' - y)^2]}{2z}\right]$$

where the coordinates of (x', y') and (x, y, z) were at the waveguide aperture and at the radiated positions, respectively.




Figure 1: Intensity x - y profiles measured at $z = 150$ mm in the tilted injection.

Figure 2: Intensity and phase profiles of an irradiant Φ_{21} waveguide mode in x -direction.

The orthogonality of the propagating modes in a free space comes from the parabolic equation. Since the irradiant waveguide modes $\Phi_{mn}(x,y)$ meet the parabolic equation, the functions Φ_{mn} were orthogonal bases in the free-space propagation within the paraxial approximation. The radiated field $E(x,y)$ was expressed with the orthogonal bases as, $E(x,y) = \sum_{mn} C_{mn} \Phi_{mn}(x,y)$ where C_{mn} is a complex fraction of the (m,n) mode.

IV. MODE CONTENT ANALYSIS

The irradiant waveguide modes Φ_{mn} were calculated by the Kirchhoff integral in the paraxial approximation. Figure 2 shows the intensity and phase profiles of the Φ_{21} mode in x -direction at $y=0$ cut. There was the phase jump in the $\pm x$ direction. The beam center offset, shown in Fig.1, mainly came from the interference between the Φ_{11} and Φ_{21} modes. The phase profile of the Φ_{11} mode was isotropically distributed and approximately flat. The asymmetric phase profile of the Φ_{21} mode caused the asymmetric interference with the Φ_{11} mode in the x -direction, and induced the intensity profile with the beam-offset in the x -direction. On the interference point of view, the beam size was also affected by mixing between the Φ_{11} and Φ_{1n} modes.

The amplitude profile radiated from the waveguide can be expressed with mode expansion by the irradiant waveguide modes. The mode content analysis resulted in a root finding of the complex fractions that can explain the measured amplitude profile. The iteration process was applied to find the complex fractions in the mode expansion for the intensity profile at $z=150$ mm in Fig.1. The complex fractions C_{11} and C_{21} were initially defined in the iteration process, assuming that the observed beam-offset was explained only by the interference between the Φ_{11} and Φ_{21} modes. The complex fractions of the other irradiant waveguide mode were assumed to be zero. The complex fractions C_{11} , C_{21} and C_{12} were retrieved in the iteration process on assumption of the initial complex fractions. Figure 3 shows an evolution of a difference ϵ between the measured and reconstructed amplitude profiles in the iteration process. The difference ϵ was defined to be integrated value in the x - y plane. The difference ϵ was reduced and converged in the iteration process well. The mode content of the beam was evaluated as 0.69, 0.13 and 0.08 for the Φ_{11} , Φ_{21} and Φ_{12} modes in the previous mode content analysis using the phase measurements and the phase retrieval process [3]. The main modes were the Φ_{11} and Φ_{21} mode in the beam. The rather small difference ϵ , resulting from good assumption of the main complex fractions C_{11} and C_{21} , may be easily converged in the iteration. In order to check availability of this approach, the iteration process starting from only C_{11} (*i.e.* $C_{21} = 0$) was tested. Figure 4 shows the evolution of the difference ϵ in the iteration on initial assumption of only C_{11} . Although the initial difference ϵ was large, the difference ϵ was well reduced and converged in the iteration process. Finally, the same complex fractions were retrieved as those under the main mode assumption. This iteration process to




Figure 3: Difference ϵ in the iteration process on assumption of the main irradiant waveguide modes.

Figure 4: Difference ϵ in the iteration process starting from only C_{11} .

find the complex fractions was confirmed to be an appropriate approach.

Figure 5 shows the measured and reconstructed amplitude profile at the propagating $z=150$ mm position. The profile reconstructed from the evaluated complex fractions was coincided with the measured profile. The mode content analyzed from the obtained complex fractions were 0.67, 0.13 and 0.05 for the Φ_{11} , Φ_{21} and Φ_{12} modes, indicating a good agreement with the previous mode content analysis. Figure 6 shows the measured and reconstructed amplitude profile at the propagating $z=200$ mm position. The measured amplitude profiles at $z=150$ and 200 mm may not perfectly explained by the evaluated complex fractions C_{11} , C_{21} and C_{12} . More various modes in a few amplitude profiles along the propagation should be included in the analysis.




Figure.5: Measured and reconstructed amplitude profiles in the x - and y -directions measured at $z=150$ mm.




Figure.6: Measured and reconstructed amplitude profiles in the x - and y -directions measured at $z=200$ mm.

- [1] H. Idei *et al.*, IEEE Trans. Microw. Theory Tech. **54**, 3899-3905 (2006).
- [2] N.L. Aleksandrov *et al.*, Int. J. of Infrared and Millimeter Waves **18** 1505-16 (1997).
- [3] H. Idei *et al.*, Proceeding of the IRMMW-THz 2007 Conf., MonA3-3.